

# Pump Switch Overview

Wide-angle pump switches directly control pumps up to 3 HP at 250 VAC. Each switch features an adjustable pumping range.

Pump Switch	Type of Activation	Pump Control	Max Pump Run Current	Max Pump Start Current	Pumping Range
 <b>Medium Duty Wide-Angle Mechanical</b>	Mechanically Activated	Use pump run and start current	13A, 125V 12A, 250V	78A, 125V 72A, 250V	8 - 36 in (20 - 91 cm)
 <b>Heavy Duty Wide-Angle Mechanical</b>	Mechanically Activated	3/4 HP, 115V 2 HP, 230V	15A, 115V 15A, 230V	85A, 115V 85A, 230V	7 - 36 in (18 - 91 cm)
 <b>Medium Duty Wide-Angle Mercury</b>	Mercury Activated	1 HP, 115V 2 HP, 230V	15A, 115V 12A, 230V	55A, 115V 35A, 230V	6.5 - 13.5 in (16.5 - 34 cm)
 <b>Medium Duty Wide-Angle Mini Mercury</b>	Mercury Activated	1/2 HP, 115V 1 HP, 230V	13A, 115V 8A, 230V	40A, 115V 20A, 230V	6.5 - 19 in (16.5 - 48 cm)
 <b>Medium Duty Limited Space</b>	Mechanically Activated	1/2 HP, 115V 1 HP, 230V	13A, 115V 12A, 230V	60A, 115V 60A, 230V	.75 - 6.5 in (2 - 17 cm)
 <b>Medium Duty Wide-Angle Dual</b>	Mechanically Activated	15 FLA, 90LRA 115V or 230V	15A, 115V 15A, 230V	90A, 115V 90A, 230V	3 - 48 in (7.6 - 122 cm)
 <b>High Temperature Pump Switch</b>	Mechanically Activated	Use pump run and start current	13A, 125V 12A, 250V	78A, 125V 72A, 250V	8 - 36 in (20 - 91 cm)



**CSI Controls**®



Toll Free: 888-342-5753  
customer.service@sjeinc.com  
www.csicontrols.com

California Prop 65 requires the following:  WARNING Cancer and Reproductive Harm - www.P65Warnings.ca.gov

9500491A 06/21  
© 2021 SJE, Inc. All Rights Reserved.  
CSI CONTROLS is a trademark of SJE, Inc.