






Pump Switch Overview

Wide-angle pump switches directly control pumps up to 3 HP at 250 VAC. Each switch features an adjustable pumping range.

Pump Switch	Type of Activation	Pump Control	Max Pump Run Current	Max Pump Start Current	Pumping Range
 Medium Duty Wide-Angle Mechanical	Mechanically Activated	Use pump run and start current	13A, 125V 12A, 250V	78A, 125V 72A, 250V	8 - 36 in (20 - 91 cm)
 Heavy Duty Wide-Angle Mechanical	Mechanically Activated	3/4 HP, 115V 2 HP, 230V	15A, 115V 15A, 230V	85A, 115V 85A, 230V	7 - 36 in (18 - 91 cm)
 Medium Duty Limited Space	Mechanically Activated	1/2 HP, 115V 1 HP, 230V	13A, 115V 12A, 230V	60A, 115V 60A, 230V	.75 - 6.5 in (2 - 17 cm)
 Medium Duty Wide-Angle Dual	Mechanically Activated	15 FLA, 90LRA 115V or 230V	15A, 115V 15A, 230V	90A, 115V 90A, 230V	3 - 48 in (7.6 - 122 cm)
 High Temperature Pump Switch	Mechanically Activated	Use pump run and start current	13A, 125V 12A, 250V	78A, 125V 72A, 250V	8 - 36 in (20 - 91 cm)



CSI Controls®



Toll Free: 888-342-5753
customer.service@sjeinc.com
www.csicontrols.com

California Prop 65 requires the following:  WARNING Cancer and Reproductive Harm - www.P65Warnings.ca.gov

9500491B 06/22
© 2021 SJE, Inc. All Rights Reserved.
CSI CONTROLS is a trademark of SJE, Inc.